

County Surveyor's Record, Douglas County, Oregon

CHAINS	Dependent Resurvey, Subdivisional Lines, T. 24 S., R. 8 W.
38.30	Intersect SW. face of wood frame cabin, 20 x 15 ft., long side bears N. 35° W. and S. 35° E., the most southerly corner bears S. 35° E., 9 lks. distance.
41.59	<p>The $\frac{1}{4}$ sec. cor. of secs. 21 and 22, determined at record bearing and distance from the original bearing trees:</p> <p>A fotted fir stump, 40 ins. diam., bears East, 84 lks. dist., no marks remaining.</p> <p>A fir, 42 ins. diam., bears S. 75° W., 47 lks. dist., marked with old axe marks and face on opened blaze.</p> <p>At the corner point</p> <p>Set an iron post, 28 ins. long, $2\frac{1}{2}$ ins. diam., 22 ins. in the ground, with brass cap marked</p> <div style="text-align: center;"> $\frac{1}{4}$ S 21 S 22 T 24 S R 8 W 1962 </div> <p>from which new bearing trees</p> <p>A fir, 13 ins. diam., bears S. 32$\frac{1}{2}$° E., 120 lks. dist., mkd $\frac{1}{4}$ S22 BT.</p> <p>A fir, 10 ins. diam., bears S. 50$\frac{1}{4}$° W., 52 lks. dist., mkd. $\frac{1}{4}$ S21 BT.</p>
	<p>N. 1° 12' W., beginning new measurement.</p> <p>Descend 40 ft. over NW. slope, through heavy timber and moderate undergrowth.</p>
4.40	Draw, drains, S1 75° W.; asc. 25 ft. over broken SW. slope.
12.40	Top of ascent, slopes S. 60° W.; desc. 20 ft. over NW. slope.
14.10	Draw, drains S. 65° W.; asc. 30 ft. over SW. slope.
16.95	Top of ascent, slopes S. 60° W.; desc. 30 ft. over NW. slope.
18.50	Draw, drains W.; asc. 15 ft. over SW. slope.
20.80	Spur, slopes W.; desc. 420 ft. over NW. slope.
35.80	Creek, 10 lks. wide, course N. 60° E.; asc. 50 ft. over SE. slope.
38.59	<p>The cor. of secs. 15, 16, 21 and 22, determined from the remaining original bearing trees:</p> <p>A fir, 40 ins. diam., bears S. 81° E., 40 lks. dist., slope dist., 43 lks. mkd. with a healed blaze. (Record, S. 77° E., 43 lks. dist.) Reblaze and mark T24S R8W S22 BT.</p> <p>A fir, 47 ins. diam., bears S. 40° W., 40 lks. dist., no visible marks. (Record bearing, S. 42° W.) Reblaze and mark T24S R8W S21 BT.</p>